الإتصال بشبكة المعلومات الدولية ( الإنترنت ) بإستخدام جهاز ( هو او ي )

الخطوة الأولى / تعريف جهاز الإستقبال اللاسلكي الى جهاز الحاسوب . الخطوة الثانية / تكوين شبكة إتصال جديدة .

> المتطلبات : 1- جهاز حاسوب يدعم منفذ ( USB 2.0 ) . 2- نظام تشغيل ويندوز ( WIN98 ) أو أحدث . 3- القرص الضوئي ( مرفق مع جهاز الإستقبال اللاسلكي ) . 4- سلك البيانات ( مرفق مع جهاز الإستقبال اللاسلكي ) .

أولاً / تعريف جهاز الإستقبال اللاسلكي الي جهاز الحاسوب

1- ضع جهاز الحاسوب وجهاز الإستقبال اللاسلكي في وضع التشغيل
 2- قم بتوصيل سلك البيانات من جهة جهاز الإستقبال اللاسلكي فقط .
 3- قم بإدخال القرص الضوئي الى مشغل الأقراص الضوئية بالحاسوب ( CDROM DRIVER ) .
 4- إفتح الملف ( SETUP.EXE ) في القرص الضوئي فتظهر النافذة التالية :

<ul> <li>Select the language for this installation from the choices below</li> </ul>
English

5- أضغط ( نعم ) وإنتظر حتى ظهور النافذة التالية :



6- إضغط ( التالي ) وإتبع التعليمات الى أن تظهر النافذة التالية :



## 7- قم بتوصيل سلك البيانات الى منفذ ( USB ) بجهاز الحاسوب فتظهر النافذة :



8- إضغط ( التالي ) فتظهر النافذة التالية :

Found New Hardware Wizard		
	This wizard helps you install software for: TUSB3410 If your hardware came with an installation CD or floppy disk, insert it now. What do you want the wizard to do? What do you want the wizard to do? Install the software automatically [Recommended] Install from a list or specific location (Advanced) Click Next to continue.	
	< <u>B</u> ack <u>N</u> ext > Cancel	

9- إضغط ( التالي ) وإنتظر حتى تظهر النافذة التالية :

Please	select the best match	for your ha	ardware from the	list below.	
D	escription	Version	Manufacturer	Location	
	TUSB3410	1.2.10.96	Texas Instruments	c:\windows\inf\umpu	
$\leq$	TUSB3410	1.2.10.96	Texas Instruments	d:\driverfiles\winxp\u	_
	UMP 3410 Unitary Driver	1.2.0.0	Texas instruments	d:\driverfiles\win98\u	
<				<u>&gt;</u>	
	This driver is not digit Tell me why driver signing	ally signed	11		
			< Back	Next > Cano	el

−10 قم بتحديد الإختيار الثاني ( WINXP ) ثم إضغط التالي فتظهر النافذة التالية :



11 – إضغط ( المتابعة في أي حال )

Found New Hardware Wizard	
Please wait while the wizard installs the software	
TUSB3410	
umpf3410.i51 To C:\WINDOWS\system32\drivers	
(•••••••••••••••••••••••••••••••••••••	ck Next > Cancel

Found New Hardware Wizard		
	Completing the Found New Hardware Wizard The wizard has finished installing the software for: TUSB3410	
	Click Finish to close the wizard.	
	K Back Finish Cancel	

- 12- إضغط إنهاء
- 12 بمبت بهاء
   13 سيقوم النظام بتكرار هذه العملية .
   14 قم بالرجوع الى النافذة التالية وإضغط ( التالي )



15 - ستضهر النافذة التالية :



17 إضغط ( المتابعة في أي حال ) وإنتظر الى أن تظهر النافذة التالية :



18- إضغط ( إنهاء )

ثالثاً / تكوين شبكة إتصال جديدة

1- الضغط على ( إبدأ / إعدادات / لوحة التحكم / شبكات الإتصال )
 2- الضغط على ( ملف / إتصال جديد ) فتظهر نافذة جديدة كما هومبين في الشكل :



3- الضغط على ( التالي ) فتظهر النافذة التالية :



4- الضغط على ( التالي ) فتظهر النافذة التالية :

New Connection Wizard
Getting Ready The wizard is preparing to set up your Internet connection.
How do you want to connect to the Internet?
Set up my connection manually
For a dial-up connection, you will need your account name, password, and a phone number for your ISP. For a broadband account, you won't need a phone number.
○ Use the <u>C</u> D I got from an ISP
< <u>B</u> ack <u>N</u> ext > Cancel

5- يتم تحديد الخيار الثاني ( إعداد الإتصال يدوياً ) وإضغط ( التالي ) فتظهر النافذة التالية :

New Connection Wizard
Internet Connection How do you want to connect to the Internet?
Connect using a dial-up modem     This type of connection uses a modem and a regular or ISDN phone line.
Connect using a broadband connection that requires a user name and password
This is a high-speed connection using either a DSL or cable modem. Your ISP may refer to this type of connection as PPPoE.
Connect using a broadband connection that is <u>always</u> on This is a high-speed connection using either a cable modem, DSL or LAN connection. It is always active, and doesn't require you to sign in.
< <u>B</u> ack <u>N</u> ext > Cancel

6- إضغط ( التالي ) فتظهر النافذة التالية وقم بإختيار جهاز ( HUAWEI WIRELESS MODEM ):

ew Connection Wizard	
This is the device that will be used I	to make the connection.
You have more than one dial-up de	vice on your computer.
Select the devices to use in this cor	nnection:
Modem - HUAWEI WIRELE	ESS MODEM(153.6K) (COM4)
Modem - Standard 33600 b	ps Modem (COM1)
Modem - TOSHIBA Softwar	e Modem (COM3)
	< <u>B</u> ack <u>N</u> ext > Cancel

8- قم بإدخال إسم الجهاز ( CDMA ) في الخانة المبينة

ew	Connection Wizard	
C	Connection Name What is the name of the service that provides your Internet connection?	4
	Type the name of your ISP in the following box.	
	ISP Name	
<	CDMA	
	The name you type here will be the name of the connection you are creating.	
	< <u>B</u> ack Next >	Canc
2 1 1 1	الي فتظهر النافذة التالية	إضعط الد
ione Wł	Number to Dial hat is your ISP's phone number?	I)
Тур	pe the phone number below.	
	Phone number:	
<	#777	
	You might need to include a "1" or the area code, or both. If you are not sure you need the extra numbers, dial the phone number on your telephone. If you hear a modem sound, the number dialed is correct.	
		Cancel

- قم بإدخال رقم الهاتف ( 777# ) في الخانة المخصصة كما هو مبين في الشكل أعلاه : إضغط التالي فتظهر النافذة التالية : -10
  - -11

New Connection Wizar	d
Internet Account Info You will need an acc	rmation ount name and password to sign in to your Internet account.
Type an ISP accoun safe place. (If you ha	name and password, then write down this information and store it in a ve forgotten an existing account name or password, contact your ISP.)
<u>U</u> ser name:	
Password:	
<u>C</u> onfirm password:	
Use this account this computer	name and password when anyone connects to the Internet from
✓ Make this the de	ault Internet connection
	< <u>B</u> ack <u>N</u> ext > Cancel

13- إضغط الزر ( التالي ) فتظهر النافذة التالية :

New Connection Wizard	
	Completing the New Connection Wizard You have successfully completed the steps needed to create the following connection: CDMA • Make this the default connection • Share with all users of this computer • Use the same user name & password for everyone The connection will be saved in the Network Connections folder.
IVAC	Add a shortcut to this connection to my desktop
	To create the connection and close this wizard, click Finish.
	< <u>B</u> ack Finish Cancel

14- إضغط ( إنهاء ) فتظهر النافذة التالية :

Connect CDMA 🛛 🛛 🔀
User name:
<ul> <li>Save this user name and password for the following users:</li> <li>Me only</li> <li>Anyone who uses this computer</li> </ul>
Djal: #777
Dial Cancel Properties Help

14-إضغط الزر ( إتصال ) فتظهر النافذة التالية :

Connecting huawei		
3	Verifying username and password	



15 عند نجاح عملية الإتصال تظهر النافذة التالية إسفل شاشة الحاسوب :

